

DIMMER COMPATIBILITY CHART

FOR REFERENCE ONLY

Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards. Consult the dimmer manufacturer prior to installation to ensure compatibility.

MANUFACTURER	PRODUCT	PART NUMBER	DIMMED LIGHT OUTPUT RANGE
Lutron	Caséta Wireless In-Wall Dimmer (PD-6WCL)	PD-6WCL	1% - 100%
	Maestro PRO LED + Tap Dimme, 250 Watts of dimmable LED/CFL, 500 Watts of incandescent/halogen/ELV, or 400VA MLV lighting loads	MA-PRO	1% - 100%
	Maestro LED+ Dimmer Switch 150 W LED/CFL, 150W of dimmable LEDs, 600W of incandescent or halogen lighting	MACL-153M	1% - 100%
	Skylark Contour LED+ Preset Dimmer, Incandescent / Halogen, 600 W, 120 V, LED / CFL, 150 W, 120 V	CTCL-153P	1% - 100%
	Diva LED, Single Pole, 3-Way, LED+ Preset Dimmer, Incandescent / Halogen, 120 V, LED / CFL, 120 V	DVCL-153P	1% - 100%
	Skylark LED+, Single Pole, 3-Way, LED+ Dimmer, Incandescent / Halogen, 600 W, 120 V, LED / CFL, 150 W, 120 V	SCL-153P	1% - 100%
	Maestro, 600 W/600 VA Neutral Wire Dimmer, 120 V - 50/60 Hz	RRD-6ND	1% - 100%
	Preset Dimmers, Single Pole, Magnetic Low Voltage, 120 V	DVLV-600P	1% - 100%
	Ariadni® / Toggler® 600 W Incandescent/Halogen Preset Dimmer (3-Way)	AY-603P	1% - 100%
	RadioRa 3 250 W (LED/CFL)* or 500 W Incandescent/Halogen/ELV or 400 VA MLV Phase Selectable Neutral Dimmer	RRST-PRO-N	1% - 100%
Leviton	Decora Digital Dimmer Switch, Low Voltage/LED/CFL/Incandescent dimmer with Bluetooth & timer	DDE06-BLZ	1% - 100%
	Trimatron Rotary Dimmer Switch Universal Dimmer, Single pole, 600W Incandescent, 150W LED, CFL	RNL06	1% - 100%
	Decora SureSlide Dimmer Switch for Dimmable LED, Halogen, and Incandescent Bulbs	6672	5% - 100%
	Decora SureSlide Dimmer Switch for Dimmable LED, Halogen, and Incandescent Bulbs	6674	5% - 100%

***NOTE:** Refer to dimmer manufacturer's documentation for installation instructions and circuit details

Disclaimer: Minimum and maximum loads for LEDs and CFLs are given in number of lamps and may vary depending on the lamp being used. Testing conducted by ELCO Lighting is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards.

Integrating our lighting with your Smart Home System is a breeze. Simply check your Smart Home system for compatible smart switches and cross reference that with our Dimming Compatibility Chart. Once the switches are integrated with your Smart Home system your lights will be ready to go.

