

LED Exit Sign and LED Emergency Light Combo




Features

- Injection-molded thermoplastic ABC and PC housing resist impacts, scratches and corrosion.
- Red or green letters, 6" letter height with 3/4" stroke. Single or double face configuration.
- Two fully adjustable LED emergency heads.
- 120/277V AC Dual voltage operation. Low power consumption 2.8 watts at normal operation (2 x 1W heads).
- Ni-Cad Battery 4.8V 1.0Ah. 90 minutes battery backup.
- Universal back, side, or ceiling mounting.
- Housing snaps to canopy with simple twist, locking it tightly and securely.
- cUL listed.


Specifications

Voltage	120/277V
---------	----------

Options



Dimensions



Product Numbers

Item	Description	Voltage
EE86HG	Green Letters	120/277V
EE85HR	Red Letters	120/277V
EE86HRG	Red & Green Letters	120/277V